



DN-6934:B1

FSI-851(A)

**Intelligent Plug-In Ionization
Smoke Detector with FlashScan®**



Intelligent/Addressable Devices

General

The FSI-851(A) intelligent plug-in ion detectors with integral communication has features that surpass conventional detectors. Detector sensitivity can be programmed in the control panel software. Sensitivity is continuously monitored and reported to the panel. Point ID capability allows each detector's address to be set with rotary, decimal address switches, providing exact detector locations for selective maintenance when chamber contamination reaches an unacceptable level.

The FSI-851(A) ionization detector incorporates a unique single-source, dual-chamber design to respond quickly and dependably to a broad range of fires. FSI-851(A) detectors are compatible with ONYX series and CLIP series intelligent Fire Alarm Control Panels (FACPs).

FlashScan® (U.S. Patent 5,539,389) is a communication protocol developed by NOTIFIER that greatly improves the speed of communication between analog intelligent devices and certain NOTIFIER systems. Intelligent devices communicate in a grouped fashion. If one of the devices within the group has new information, the panel's CPU stops the group poll and concentrates on single points. The net effect is response speed greater than five times that of other protocols.

Features

- Sleek, low-profile design.
- Addressable-analog communication.
- Stable communication technique with noise immunity.
- Low standby current.
- Two-wire SLC connection.
- Compatible with FlashScan® and CLIP systems
- Rotary, decimal addressing (1-99 on CLIP systems, 1-159 on FlashScan systems).
- Optional remote, single-gang LED accessory, RA100Z(A).
- Dual LED design provides 360° viewing angle.
- Visible bicolor LEDs blink green every time the detector is addressed, and illuminate steady red on alarm.
- Remote test feature from the panel.
- Walk test with address display (an address of 121 will blink the detector LED: 12-(pause)-1) (FlashScan® systems only).
- Built-in functional test switch activated by external magnet.
- Built-in tamper-resistant feature.
- Sealed against back pressure.
- Constructed of off-white plastic, designed to commercial standards, and offers an attractive appearance.
- 94-5V plastic flammability rating.
- SEMS screws for wiring of the separate base.
- Optional relay, isolator, or sounder bases.
- Listed to UL 268.



B210-1951.jpg

FSI-851(A) in B210LP(A) Base

Specifications

Sensitivity: 0.5% to 2.5% per foot obscuration

Size: 2.0" (51 mm) high; base determines diameter.

– **B210LP(A):** 6.1" (15.5 cm) diameter.

– **B501(A):** 4.1" (10.4 cm) diameter.

– **B200S(A):** 6.875" (17.46 cm) diameter.

– **B200SR(A):** 6.875" (17.46 cm) diameter.

– **B224RB(A):** 6.2" (15.748 cm) diameter.

Shipping Weight: 5.4 oz. (153 g).

Operating Temperature: 0°C to 49°C (32°F to 120°F).

UL/ULC-Listed Velocity Range: ION: 0 – 1200 ft./min. (365.76 m/min.).

Relative Humidity: 10% – 93% noncondensing.

ELECTRICAL SPECIFICATIONS

Voltage Range: 15 - 32 volts DC peak.

Standby Current (max. avg.): 300 µA

LED Current (max.): 6.5 mA @ 24 VDC ("ON").

Installation

FSI-851(A) plug-in detectors use a separate base to simplify installation, service, and maintenance. A special tool allows maintenance personnel to plug in and remove detectors without using a ladder.

Mount base (all base types) on an electrical backbox which is at least 1.5" (3.81 cm) deep. For a chart of compatible junction boxes, see DN-60054.

NOTE: 1) Because of the inherent supervision provided by the SLC loop, end-of-line resistors are not required. Wiring "T-taps" or branches are permitted for Style 4 (Class "B") wiring. 2) When using relay or sounder bases, consult the ISO-X(A) installation sheet 156-1380 for device limitations between isolator modules and isolator bases.





Agency Listings and Approvals

These listings and approvals apply to the modules specified in this document. In some cases, certain modules or applications may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- **UL Listed:** S1115.
- **ULC Listed:** S1115 (FSI-851A).
- **CSFM:** 7271-0028:201.
- **MEA:** 321-02-E.
- **Maryland State Fire Marshal:** Permit #2140.
- **BSMI:** CI313066760014.
- **U.S. Coast Guard:** 161.002/42/1 (NFS-640); 161.002/50/0 (NFS2-640/NFS-320/NFS-320C, excluding B210LP(A)).
- **Lloyd's Register:** 11/600013 (NFS2-640/NFS-320/NFS-320C, excluding B210LP(A)).
- **FM Approved.**

Product Line Information

NOTE: "A" suffix indicates ULC Listed model.

FSI-851: Low-profile intelligent ionization sensor. Must be mounted to one of the bases listed below.

FSI-851A: Same as FSI-851 but with ULC Listing.

INTELLIGENT BASES

NOTE: "A" suffix indicates ULC Listed model.

NOTE: For details on intelligent bases, see DN-60054.

B210LP(A): Standard U.S. flanged low-profile mounting base.

B210LPBP: Bulk pack of B210LP; package contains 10.

B501(A): Standard European flangeless mounting base.

B501BP: Bulk pack of B501; package contains 10.

B200S(A): Intelligent, programmable sounder base capable of producing sound output in high or low volume with ANSI Temporal 3, ANSI Temporal 4, continuous tone, marching tone, and custom tone.

B200SR(A): Intelligent sounder base capable of producing sound output with ANSI Temporal 3 or continuous tone. Replaces B501BH series bases in retrofit applications.

B224RB(A): Plug-in System Sensor **relay** base. Screw terminals: up to 14 AWG (2.0 mm²). Relay type: Form-C. Rating: 2.0 A @ 30 VDC resistive; 0.3 A @ 110 VDC inductive; 1.0 A @ 30 VDC inductive.

B224BI(A): Plug-in System Sensor **isolator** detector base. Maximum 25 devices between isolator base.

ACCESSORIES

F110: Retrofit flange to convert B210LP(A) to match the B710LP(A) profile, or to convert older high-profile bases to low-profile.

F110BP: Bulk pack of F110; package contains 15.

F210: Replacement flange for B210LP(A) base.

RA100Z(A): Remote LED annunciator. 3 – 32 VDC. Mounts to a U.S. single-gang electrical box. For use with B501(A) and B210LP(A) bases only.

SMB600: Surface mounting kit.

M02-04-00: Test magnet.

M02-09-00: Test magnet with telescoping handle.

XR2B: Detector removal tool. Allows installation and/or removal of detector heads from bases in high ceiling applications.

XP-4: Extension pole for XR2B. Comes in three 5-foot (1.524 m) sections.

T55-127-010: Detector removal tool without pole.

BCK-200B: Black detector covers; package contains 10.

WCK-200B: White detector covers; package contains 10.

NOTIFIER® and FlashScan® are registered trademarks of Honeywell International Inc.

©2012 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.



This document is not intended to be used for installation purposes.
We try to keep our product information up-to-date and accurate.
We cannot cover all specific applications or anticipate all requirements.
All specifications are subject to change without notice.

For more information, contact Notifier. Phone: (203) 484-7161, FAX: (203) 484-7118.
www.notifier.com



Made in the U.S. A.

