



AH-0218

AH-0218 AH-9719

Fire Alarm Bell & Indicating Lamp



AH-9719

AH-0218 Fire Alarm Bell 6"

- High efficiency low current consumption on 24VDC motorized bells.
- Terminals will accept 2.5mm cables.
- Simple installation via multi-fixing base plate for all types of location.
- Fitted with two series diodes for fault monitoring.
- Option of customized discs printed with company name and logo.
- *12VDC bells are also available.*

AH-9719 Fire Indicating Lamp

- Uses white bulb (or low current LED) and installed inside the red lamp cover.
- When lit, it is clear visible within 10 meters.

Specifications

| Model | AH-0218 |
|-------------------|--|
| Dimensions | ø6" (152mm) x 56mm(H) |
| Voltage | 24V DC |
| Current | 25mA |
| Sound Output | 93dB @1M |
| Movement | Motor, Pinion and striker |
| Movement Features | DC Motor, acetal gear wheel, steel striker |
| Gong | Steel, secured with phillips screw |
| Base Plate | Molded black polycarbonate |
| Material | Steel plate |
| Weight | About 850g |

Specifications

| Model | AH-9719 |
|---------------------|------------------------|
| Dimensions | 90mm(Dia.) x 70mm(H) |
| Consumption Current | 24V DC 60mA / LED 20mA |
| Bulb | 30V/2W bulb or LED |
| Material | Fire-proof plastic |
| Weight | About 70g |

