



ENERGY 650 START 230-400V 12-24V



Overview

ENERGY 650 START 230-400V 12-24V

cod. 829385

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.



3 PH 230V-400V



TRACTOR



VAN



REMOTE CONTROLS



SMALL VAN



CE MARKING



CAR



EXCAVATOR



EAC CERTIFICATION



BOAT

Technical data



CODE 829385



EFFECTIVE CHARGING CURRENT 100 A



ADJUSTMENT POSITIONS 5



THREE PHASE MAINS VOLTAGE 230 / 400 V



RATED CHARGE CURR. EN60335-2-29 80 A



DIMENSIONS 36,5 x 46 x 75,5 cm



ENERGY 650 START 230-400V 12-24V

MAINS FREQUENCY 50 / 60 Hz	START CURRENT 1V/C EN60335-2-29 640 A	WEIGHT 38 kg
CHARGE POWER 2,5 KW	MAX STARTING CURRENT 1000 A	EAN CODE 800489774452 0
START POWER 20 KW	MIN. RATED REFERENCE CAPACITY 20 A	PIECES/PALLET 9 pz/pallet
CHARGING VOLTAGE 12 / 24 V	MAX RATED REFERENCE CAPACITY 1200 / 800 A	PIECES/PALLET - B 6 pz/pallet-B

Included Accessories

REMOTE CONTROL 6 M - 123993