



ENERGY 1000 START 230-400V



Overview

ENERGY 1000 START 230-400V

cod. 829008

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.



3 PH 230V-400V



TRACTOR



VAN



REMOTE CONTROLS



SMALL VAN



CE MARKING



CAR



EXCAVATOR



EAC CERTIFICATION



BOAT

Technical data



CODE 829008



EFFECTIVE CHARGING CURRENT 100 A



ADJUSTMENT POSITIONS 5



THREE PHASE MAINS VOLTAGE 230 / 400 V



RATED CHARGE CURR. EN60335-2-29 80 A



DIMENSIONS 38 x 56 x 88,5 cm



ENERGY 1000 START 230-400V

MAINS FREQUENCY 50 / 60 Hz	START CURRENT 1V/C EN60335-2-29 640 A	WEIGHT 45 kg
CHARGE POWER 2,5 KW	MAX STARTING CURRENT 1000 A	EAN CODE 800489736539 8
START POWER 20 KW	MIN. RATED REFERENCE CAPACITY 20 A	PIECES/PALLET 6 pz/pallet
CHARGING VOLTAGE 12 / 24 V	MAX RATED REFERENCE CAPACITY 1200 / 800 A	PIECES/PALLET - B 4 pz/pallet-B

Included Accessories

CABLE 25 MMQ 2,5 M - 123456
CABLE 25 MMQ 3 M - 123467
REMOTE CONTROL 6 M - 123993

POSITIVE CLAMP (+) - 712025
WORK CLAMP - 712026