



## ENERGY 1500 START 230-400



### Overview

#### ENERGY 1500 START 230-400

cod. 829009

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.



3 PH 230V-400V



TRACTOR



VAN



REMOTE CONTROLS



SMALL VAN



CE MARKING



CAR



EXCAVATOR



EAC CERTIFICATION



BOAT

### Technical data



CODE 829009



EFFECTIVE CHARGING CURRENT 150 / 250 A



ADJUSTMENT POSITIONS 6



THREE PHASE MAINS VOLTAGE 230 / 400 V



RATED CHARGE CURR. EN60335-2-29 130 / 220 A



DIMENSIONS 38 x 56 x 88,5 cm



## ENERGY 1500 START 230-400

MAINS FREQUENCY 50 / 60 Hz	START CURRENT 1V/C EN60335-2-29 1000 / 1300 A	WEIGHT 69 kg
CHARGE POWER 7 KW	MAX STARTING CURRENT 1700 / 2000 A	EAN CODE 800489736540 4
START POWER 44 KW	MIN. RATED REFERENCE CAPACITY 70 A	PIECES/PALLET 4 pz/pallet
CHARGING VOLTAGE 12 / 24 V	MAX RATED REFERENCE CAPACITY 2000 / 4000 A	PIECES/PALLET - B 6 pz/pallet-B

### Included Accessories

REMOTE CONTROL 6 M - 123993

CABLE 50MMQ 3M-WORK CLAMP - 713260

CABLE 50MMQ 3M-POSITIVE CLAMP-EYELET Ø10 - 713162