

**Mini Sound Level Meter FM-7901A/7901C**

The sound level meter is designed to meet the measurement requirements of safety engineers, health, industrial safety offices and sound quality control in various environments like factory, school, construction, etc.

**FEATURES** ↘

- ▶ Portable, nice, easy operation
- ▶ MAX/MIN data hold
- ▶ Backlight LCD display
- ▶ Low battery indication
- ▶ Auto power off



**Specifications**

Model	FM-7901A	FM-7901C
Measuring Level Range	30~130dB	
Frequency Weighting	dBA	dBC
Operating Conditions	-20~60°C ; <90%RH (Non-condensation)	
Storage Conditions	-20~60°C ; < 75%RH	
Accuracy	±1.4dB	
Resolution	0.1dB	
Frequency Range	31.5Hz~8KHz	
Dynamic Range	50dB	
Data Update	0.5 Second	
Microphone	1/2 inch electret condenser	



Dimension(L\*W\*H): 144\*55\*38mm

Weight: 149g

Accessories: User's manual, 9V battery, windscreen, Blister card with clamshell.